



MB39C831

Ultra Low Voltage Boost Power Management IC for Solar/Thermal Energy Harvesting Datasheet

Description

The MB39C831 is the high-efficiency synchronous rectification boost DC/DC converter IC which efficiently supplies energy getting from the solar cell with the single cell or multiple cells, or from the thermoelectric generator (TEG) to the Li-ion battery.

It contains the function to control the DC/DC converter output following the maximum power point of the solar cell (MPPT: Maximum Power Point Tracking) and the protection function to charge the Li-ion battery safely.

It is possible to start-up from 0.35 V using the low-voltage process and adapts the applications which the single cell solar cell is treated as the input.

Features

- Operation input voltage range : 0.3V to 4.75V
- Output voltage adjustment range : 3.0V to 5.0V
- Minimum input voltage at start-up : 0.35V
- Quiescent Current (No load) : 41 μ A
- Input peak current limit : 200 mA
- Built-in MPPT
- Charge voltage to the Li-ion battery/current protection function built in
- Improvement of the efficiency during the low-output power according to the auto PFM/PWM switching mode

Applications

- Solar energy harvesting
- Thermal energy harvesting
- Li-ion battery using the single cell or multiple cells' solar cell/Super Capacitor Charger
- Portable audio players
- Cellular phone
- eBook
- Electronic dictionary
- Wireless remote controllers
- Sensor node

Note: This product supports the web-based design simulation tool, Easy DesignSim.

It can easily select external components and can display useful information.


Please access from <http://cypress.transim.com/login.aspx>

Contents

1. Pin Assignments	3
2. Pin Descriptions	4
3. Block Diagram	5
4. Absolute Maximum Ratings	6
5. Recommended Operating Conditions	7
6. Electrical Characteristics	7
6.1 Electrical Characteristics of Constant Voltage Mode	7
6.2 Electrical Characteristics of Charge Mode	8
6.3 Electrical Characteristics of Boost DC/DC Converter	8
7. Function	9
7.1 Outline of Operation	9
7.2 Start-up/Shut-down Sequence	9
7.3 MPPT Control	12
7.4 Function Description	14
8. Typical Applications Circuit	18
9. Application Notes	21
10. Typical Characteristics	23
11. Layout for Printed Circuit Board	28
12. Usage Precaution	29
13. Ordering Information	29
14. Marking	29
15. Product Labels	30
16. Recommended Mounting Conditions	34
17. Package Dimensions	36
Major Changes	37

1. Pin Assignments

Figure 1-1 Pin Assignments




2. Pin Descriptions

Table 2-1 Pin Descriptions

Pin No.	Pin Name	I/O	Description
1	S2	I	Input pin for preset output voltage setting and MPPT setting
2	S1	I	Input pin for preset output voltage setting and MPPT setting
3	S0	I	Input pin for preset output voltage setting and MPPT setting
4	ENA	I	DC/DC converter control input pin
5	MPPT_ENA	I	MPPT control input pin
6	SGND1	-	Analog ground pin
7	SGND3	-	Analog ground pin
8, 9, 10, 11	N.C.	-	Non connection pins (Leave these pins open.)
12	CSH0	O	Capacitor connection pin for MPPT, used only at the charge mode
13	CSH1	I	Capacitor connection pin for MPPT, used only at the charge mode
14	CSH2	I	Capacitor connection pin for MPPT, used only at the charge mode
15	MPPT_OUT	O	MPPT output pin, used only at the charge mode
16	MPPT_IN	I	MPPT input pin, used only at the charge mode
17	VOUT	O	Output pin of DC/DC converter
18	LX	I	Inductor connection pin
19	PGND2	-	Power ground pin
20	VOUT_S	I	Input pin for DC/DC converter FB
21	FB	I	Feedback input pin of DC/DC converter
22	SGND2	-	DC/DC control system ground pin
23	N.C.	-	Non connection pin (Leave this pin open.)
24	VCC	O	Control system power supply output pin
25	DET1	O	Output pin for state notification
26	DET0	O	Output pin for state notification
27	VDD	I	External power supply input pin
28	PGND1	-	Power ground pin
29	VST	O	Start-up power supply output pin
30, 31, 32, 33, 34, 35, 36, 37, 38, 39, 40	N.C.	-	Non connection pins (Leave these pins open.)

3. Block Diagram

Figure 3-1 Block Diagram




*1: Connect the Li-ion battery in the charge mode (refer to Figure 8-2)

4. Absolute Maximum Ratings

Table 4-1 Absolute Maximum Ratings

Parameter	Symbol	Condition	Rating		Unit
			Min	Max	
VDD input voltage	VDDMAX	VDD pin	-0.3	+7.0	V
VOOUT input voltage	VOOUTMAX	VOOUT, VOOUT_S pins	-0.3	+7.0	V
Input pin input voltage	VINPUTMAX	MPPT_ENA, ENA, S2, S1, S0, CSH0, CSH1, CSH2, MPPT_IN, MPPT_OUT pins	-0.3	VCC pin voltage +0.3 ($\leq +7.0$)	V
Power dissipation	PD	$T_a \leq +25^\circ\text{C}$	-	2500 ^(*)	mW
Storage temperature	TSTG	-	-55	+125	$^\circ\text{C}$
ESD voltage1	VESDH	Human Body Model	-2000	+2000	V
ESD voltage2	VESDM	Machine Model	-200	+200	V

*1: In the case of θ_{ja} (wind speed 0m/s) $+28^\circ\text{C/W}$

Figure 4-1 Power Dissipation – Operating Ambient Temperature

WARNING:

Semiconductor devices may be permanently damaged by application of stress (including, without limitation, voltage, current or temperature) in excess of absolute maximum ratings. Do not exceed any of these ratings.

5. Recommended Operating Conditions

Table 5-1 Recommended Operating Conditions

Parameter	Symbol	Condition	Value			Unit
			Min	Typ	Max	
VDD input voltage	VVDD	VDD pin	0.3	-	4.75	V
VOOUT input voltage	VVOUT	VOOUT pin MPPT_ENA=H, ENA=H	2.55	3	5.5	V
Input pin input voltage	VINPUT	MPPT_ENA, ENA, S2, S1, S0 pins	0	-	VCC pin voltage	V
Operating ambient temperature	Ta	-	-40	-	+85	°C

WARNING:

1. The recommended operating conditions are required in order to ensure the normal operation of the semiconductor device. All of the device's electrical characteristics are warranted when the device is operated under these conditions.
2. Any use of semiconductor devices will be under their recommended operating condition.
3. Operation under any conditions other than these conditions may adversely affect reliability of device and could result in device failure
4. No warranty is made with respect to any use, operating conditions or combinations not represented on this data sheet. If you are considering application under any conditions other than listed herein, please contact sales representatives beforehand

6. Electrical Characteristics

6.1 Electrical Characteristics of Constant Voltage Mode

Table 6-1 Electrical Characteristics of Constant Voltage Mode (MPPT_ENA = L, ENA = H)

(Ta=-40°C to +85°C, VDD ≤ VOOUT - 0.25V, L=4.7μH, Cout=10μF)

Parameter	Symbol	Condition			Value			Unit
		MPPT_ENA	ENA	Other	Min	Typ	Max	
Minimum input voltage at start-up	VSTART	L	H	VDD pin, Ta = +25°C	-	0.35	0.5	V
Preset output voltage	VOOUT			S2=L, S1=L, S0=L	2.940	3.000	3.060	V
				S2=L, S1=L, S0=H	3.234	3.300	3.366	V
				S2=L, S1=H, S0=L	3.528	3.600	3.672	V
				S2=L, S1=H, S0=H	4.018	4.100	4.182	V
				S2=H, S1=L, S0=L	4.410	4.500	4.590	V
				S2=H, S1=L, S0=H	4.900	5.000	5.100	V
Current dissipation 1	IQIN			VDD, LX pin input current, VDD=0.6V, VOOUT=3.3V, IOOUT=0	-	0.75	5 ⁽¹⁾	mA
Current dissipation 2	IQOUT			VOOUT pin input current, VOOUT=3.3V, IOOUT=0	-	32	64	μA
VCC detection voltage 1	VCCDETH1			Upper threshold	2.8	2.9	3	V
	VCCDETL1	Lower threshold	2.5	2.6	2.7	V		
VOOUT detection voltage 1	VOOUTDETH1	Upper threshold	2.8	2.9	3	V		
	VOOUTDETL1	Lower threshold	2.5	2.6	2.7	V		

*1: This parameter is not be specified. This should be used as a reference to support designing the circuits.

6.2 Electrical Characteristics of Charge Mode

Table 6-2 Electrical Characteristics of Charge Mode (MPPT_ENA = H, ENA = H)

(Ta=-40°C to +85°C, VDD ≤ VOUT - 0.25V, L=4.7μH, Cout=10μF)

Parameter	Symbol	Condition			Value			Unit
		MPPT_ENA	ENA	Other	Min	Typ	Max	
Minimum input voltage at start-up	VSTART	H	H	VDD pin, Ta = +25°C	-	0.35	0.5	V
MPPT setting	MPPTSET			S2=L, S1=L, S0=L	45	50	55	%
				S2=L, S1=L, S0=H	50	55	60	%
				S2=L, S1=H, S0=L	55	60	65	%
				S2=L, S1=H, S0=H	60	65	70	%
				S2=H, S1=L, S0=L	65	70	75	%
				S2=H, S1=L, S0=H	70	75	80	%
				S2=H, S1=H, S0=L	75	80	85	%
				S2=H, S1=H, S0=H	80	85	90	%
Current dissipation 2	IQOUT			VOUT pin input current, VOUT=3.3V, IOOUT=0	-	41	82	μA
UVLO detection voltage (VDD detection voltage)	VUVLOH			Upper threshold	0.2 ^(*)	0.3 ^(*)	0.4 ^(*)	V
	VUVLOL			Lower threshold	0.1	0.2	0.3	V
VCC detection voltage 2	VCCDETH2			Upper threshold	2.5	2.6	2.7	V
	VCCDETL2			Lower threshold	2.45	2.55	2.65	V
VOUT detection voltage 2	VOUTDETH2			Upper threshold	2.5	2.6	2.7	V
	VOUTDETL2			Lower threshold	2.45	2.55	2.65	V
VOUT detection voltage 3	VOUTDETH3	Upper threshold	3.88	4	4.12	V		
	VOUTDETL3	Lower threshold	3.58	3.7	3.82	V		

*1: This parameter is not be specified. This should be used as a reference to support designing the circuits.

6.3 Electrical Characteristics of Boost DC/DC Converter

Table 6-3 Electrical Characteristics of Boost DC/DC Converter

(Ta=-40°C to +85°C, VDD ≤ VOUT - 0.25V, L=4.7μH, Cout=10μF)

Parameter	Symbol	Condition			Value			Unit
		MPPT_ENA	ENA	Other	Min	Typ	Max	
LX peak current	ILIMIN_A	L or H	H	LX pin input current	-	200	-	mA
Maximum output current	IOOUT			VDD=0.6V, VOUT=3.3V	8	-	-	mA
				VDD=3.0V, VOUT=3.3V	80	-	-	mA
Oscillation frequency	FOSC			PWM mode	0.87	1	1.13	MHz
Line regulation	VLINE			0.4V ≤ VDD ≤ VOUT - 0.25V, IOOUT=0	-	-	0.5	%
Load regulation	VLOAD			VDD=0.6V, VOUT=3.3V, IOOUT=0 to 8mA	-	-	0.5	%

7. Function

7.1 Outline of Operation

MB39C831 is the boost DC/DC converter which has the function controls for the synchronous rectification operation of the integrated FET using the frequency set by the built-in oscillator. The converter operates in PFM at light load currents.

This converter is equipped with a constant voltage mode (MPPT_ENA = L) and a charge mode (MPPT_ENA = H).

Constant voltage mode: An output terminal VOUT outputs a constant voltage set by the S2, S1 and S0 pins.

Charge mode : The input voltage (VIN) is adjusted by following the MPPT value set by the S2, S1 and S0 pins, and a Li-ion battery can be charged.


7.2 Start-up/Shut-down Sequence

Constant Voltage Mode: MPPT_ENA = L, ENA = H

In order to operate the constant voltage mode, it supposes that to connect ceramic capacitor, electrolytic capacitor, tantalum capacitor, electric double layered capacitor, and so on, to VCC pin. See Figure 11-1 circuit to use the constant voltage mode.

The constant voltage mode is necessary to set MPPT_ENA = L and ENA = H. MPPT_ENA pin is connected to GND, and ENA pin is connected to VCC pin. See Figure 10-1 Start-up/shut-down sequences of constant voltage mode.

Figure 7-1 Start-up/Shut-down Sequences of Constant Voltage Mode (MPPT_ENA=L, ENA=H)



[1] When 0.35V (Minimum input voltage at start-up: VSTART) or higher voltage is applied to the VDD pin, the start-up circuit activates charging the VCC capacitor C2 (see Figure 3-1).

[2] When the VCC reaches 2.9V (upper threshold of VCC detection voltage 1: VCCDETH1), the operation of the start-up circuit stops, then the DC/DC converter activates charging the VOUT capacitor C3 (see Figure 3-1).

[3] When the VCC reaches less than 2.6V (lower threshold of VCC detection voltage 1: VCCDETL1) by the internal consumption current, the start-up circuit operates again, and this sequence is repeated until the VOUT becomes 2.9V (upper threshold of VOUT detection voltage 1: VOUTDETH1).

[4] When the VOUT reaches 2.9V (upper threshold of VOUT detection voltage 1: VOUTDETH1), the internal switch SW1 (see Figure 3-1) between VCC and VOUT is turned on, and then the VCC and the VOUT are connected internally. While the DC/DC converter is continuously operated, charging the VOUT capacitor C3 to the preset voltage setting by S2, S1, and S0 pins is performed.


[5] When the VDD falls and reaches 0.3V (VDD input voltage: VVDD) or less, the voltage of the VOUT and VCC starts to decrease.

[6] After that the VOUT voltage reaches 2.6V (lower threshold of VOUT detection voltage 1: VOUTDETL1) or the VCC voltage reaches 2.6V (lower threshold of VCC detection voltage 1: VCCDETL1), and then the internal switch SW1 between VCC and VOUT is turned off, and the VCC and the VOUT are disconnected internally.

Charge Mode: MPPT_ENA = H, ENA = H

In order to operate the charge mode, it supposes that to connect lithium ion secondary batteries, and so on, to VCC pin. See Figure 11-2 circuit to use the charge mode.

The charge mode is necessary to set MPPT_ENA = H and ENA = H. Both MPPT_ENA and ENA are connected to the VCC pin, and a Li-ion battery should be connected to the VOUT pin to make the VOUT $\geq 2.6V$ (upper threshold of VOUT detection voltage 2: VOUTDETH2). See Figure 10-2 Start-up/shut-down sequences of charge mode.

Figure 7-2 Start-up/Shut-down Sequences of Charge Mode (MPPT_ENA = H, ENA=H)


[1] When 0.35V (Minimum input voltage at start-up: VSTART) or higher voltage is applied to the VDD pin, the start-up circuit activates charging the VCC capacitor C2 (see Figure 3-1).

[2] When the VCC reaches 2.6V (upper threshold of VCC detection voltage 2: VCCDETH2) and the VOUT is higher than 2.6V (upper threshold of VOUT detection voltage 2: VOUTDETH2), the operation of the start-up circuit stops and the internal switch SW1 (see Figure 3-1) between VCC and VOUT is turned on. Then the DC/DC converter activates charging the Li-ion battery (see Figure 3-1), and the MPPT control starts at the same time.

[3] While the DC/DC converter is continuously operated, the voltage of VDD is controlled to the MPPT value setting by S0, S1, and S2 pins. (For more detail, refer to Chapter 7.3).

[4] When the voltage of the Li-ion battery reaches 4V (upper threshold of VOUT detection voltage 3: VOUTDETH3), the charging of the Li-ion battery stops. When the voltage of the Li-ion battery drops and reaches 3.7V (lower threshold of VOUT detection voltage 3: VOUTDETL3), the charging of the Li-ion battery starts again.

[5] When the VDD voltage drops and reaches 0.2V (lower threshold of UVLO detection voltage: VUVLOL), the operation of the DC/DC converter stops, and then the voltage of the VOUT and VCC starts to decrease.

[6] The VOUT voltage reaches 2.55V (lower threshold of VOUT detection voltage 2: VOUTDETL2) or the VCC voltage reaches 2.55V (lower threshold of VCC detection voltage 2: VCCDETL2, and then the internal switch SW1 between VCC and VOUT is turned off, and the VCC and the VOUT are disconnected internally to protect the Li-ion battery from an over-discharge.

7.3 MPPT Control

In general, the voltage of a solar cell varies depending on the load current. The operating point where the power becomes the maximum is called the optimum operating point. The control which tracks the optimum operating point is called the MPPT (Maximum Power Point Tracking) control.


MPPT Values Setting

The voltage where the power becomes the maximum is called the power maximum voltage, and the voltage with no load is called the release voltage. The comparison between the power maximum voltage and the release voltage is defined as the MPPT values.

In the charge mode, the input voltage (VDD) is adjusted and the DC/DC converter operates while tracking the MPPT value setting by the S2, S1 and S0 pins.

When in use, set the MPPT value after confirming the voltage dependency of the solar cell power.

Figure 7-3 MPPT Control



MPPT Operation

When setting the charge mode, the internal pulse frequency is determined by the values of the capacitors C5/C6 and C7/C8 (see Figure 3-1), which are connected to the CSH1 pin, and the CSH2 pin.

During the period of high level of the internal pulse setting by the capacitors C5/C6 connected to the CSH1 pin, the release voltage is measured. The capacitors C5/C6 latch the measured voltage level, the release voltage.


During the period of low level of the internal pulse setting by the capacitors C7/C8 connected to the CSH2 pin, the charge current is determined in order to make the VDD pin's voltage equal to the MPPT setting voltage, then the charging operation starts up. The MPPT setting voltage is calculated by the following equation.

MPPT setting voltage = Release voltage × MPPT value (refer to Table 7-3 MPPT control)

When using the recommended parts, the frequency is set to 0.35Hz with 5% duty.

If not using the recommended parts, please be aware of the following points.

1. In general, laminated capacitances have leak current. If the inside pulse cycle setting by the capacitors
2. C7/C8 were set too long, the voltage level of the capacitors C5/C6 would drop. There is a possibility that
3. the MPPT value cannot be set correctly.
4. If the period of high level of inside pulse is set too short, setting by the capacitors C5/C6, the MPPT value
5. cannot be set correctly due to a lack of the measurement time of the release voltage.

Figure 7-4 MPPT Operation


7.4 Function Description

Mode control

The mode is controlled by the MPPT_ENA pin. There are the charge mode and constant voltage mode, which also determine the presence or absence of The MPPT, the UVLO, the VCC detecting, and the VOUT detecting functions. Set the MPPT_ENA pin according to an application.

And also, the DC/DC converter is controlled by the ENA pin, transfer in operating state of Table10-1.

Table 7-1 Mode Control

Mode	Input Signal		Operating State	Function							
	MPPT_ENA pin	ENA Pin		UVLO	MPPT	VCC detection 1	VCC detection 2	VOUT detection 1	VOUT detection 2	VOUT detection 3	VOUT-VDD voltage reverse detection
Constant voltage	L	L	VOUT output stop	OFF	OFF	ON	OFF	ON	OFF	OFF	OFF
		H	VOUT output enabled	OFF	OFF	ON	OFF	ON	OFF	OFF	OFF
Charge	H	L	Charge stop	ON	ON	OFF	ON	OFF	ON	ON	ON
		H	Charge enabled	ON	ON	OFF	ON	OFF	ON	ON	ON

Changing Setting Method of Preset Output Voltage & MPPT Setting

The state is controlled by the MPPT_ENA, the ENA, the S2, S1, and S0 pins.

The preset output voltage can be set in the constant voltage mode, set the MPPT_ENA = L and the ENA =H, and then set it by the S2, S1, and S0 pins.

The MPPT value can be set in the charge mode, set the MPPT_ENA = H and the ENA =H, and then set it by the S2, S1, and S0 pins.

Table 7-2 Changing Preset Output Voltage in Constant Voltage Mode (MPPT_ENA = L, ENA = H)

Input Signal			Control		
MPPT_ENA pin	ENA pin	S2 pin	S1 pin	S0 pin	Preset Output Voltage (V)
L	H	L	L	L	3.0
		L	L	H	3.3
		L	H	L	3.6
		L	H	H	4.1
		H	L	L	4.5
		H	L	H	5.0
		H	H	L	Setting prohibited
		H	H	H	Setting prohibited

Table 7-3 Changing MPPT Setting in Charge Mode (MPPT_ENA = H, ENA = H)

		Input Signal			Control
MPPT_ENA pin	ENA pin	S2 pin	S1 pin	S0 pin	MPPT Values
H	H	L	L	L	50%
		L	L	H	55%
		L	H	L	60%
		L	H	H	65%
		H	L	L	70%
		H	L	H	75%
		H	H	L	80%
		H	H	H	85%

VCC Detection1, 2 (VCC Detection Voltage1, 2): VCC Voltage Protection

This function works with both the constant voltage mode (MPPT_ENA =L) and the charge mode (MPPT_ENA =H).

■ Constant voltage mode (MPPT_ENA =L)

The detection that the VCC pin is equal to the threshold voltage (VCCDETH1 = 2.9V) or higher is the source to start the DC/DC converter operation. It's a factor to turn on the internal switch between VCC and VOUT.

It has the hysteresis, and the detection that the VCC pin is equal to the threshold voltage (VCCDETL1 = 2.6V) or lower is the source to stop the DC/DC converter operation. It's a factor turn off the internal switch between VCC and VOUT.

When the VCC pin becomes higher than the threshold voltage (VCCDETH1 = 2.9V) again, this function is repeated.

■ Charge mode (MPPT_ENA =H)

The detection that the VCC pin is equal to the threshold voltage (VCCDETH2 = 2.6V) or higher is the source to start the DC/DC converter operation. It's a factor turn on the internal switch between VCC and VOUT.

It has the hysteresis, and the detection that the VCC pin is equal to the threshold voltage (VCCDETL2 = 2.55V) or lower is the source to stop the DC/DC converter operation. It's a factor turn off the internal switch between VCC and VOUT.

When the VCC pin becomes higher than the threshold voltage (VCCDETH2 = 2.6V) again, this function is repeated.

VOUT Detection1, 2 (VOUT Detection Voltage1, 2)

This function works with both the constant voltage mode (MPPT_ENA =L) and the charge mode (MPPT_ENA =H).

■ Constant voltage mode (MPPT_ENA =L)

The detection that the VOUT pin is equal to the threshold voltage (VOUTDETH1 = 2.9V), and it's a factor to turn on the internal switch between VCC and VOUT.

It has the hysteresis, and the detection that the VOUT pin is equal to the threshold voltage (VOUTDETL1 = 2.6V), and it's a factor to turn off the internal switch between VCC and VOUT.

When the VOUT pin becomes higher than the threshold voltage (VOUTDETH1 = 2.9V) again, this function is repeated.

■ Charge mode (MPPT_ENA =H)

The detection that the VOUT pin is equal to the threshold voltage (VOUTDETH2 = 2.6V) or higher is the source to start the DC/DC converter operation. It's a factor turn on the internal switch between VCC and VOUT.

It has the hysteresis, and the detection that the VOUT pin is equal to the threshold voltage (VOUTDETL2 = 2.55V) or lower is the source to stop the DC/DC converter operation. It's a factor turn off the internal switch between VCC and VOUT.

When the VOUT pin becomes higher than the threshold voltage (VOUTDETH2 = 2.6V) again, this function is repeated.

VOUT Detection3 (VOUT Detection Voltage3)

This function works with the charge mode (MPPT_ENA =H).

When the VOUT pin becomes higher than the threshold voltage (VOUTDETH3 = 4V), the DC/DC converter stops the operation.

It has the hysteresis, and when the VOUT pin becomes lower than the threshold voltage (VOUTDETL3 =3.7V), the DC/DC converter restarts the operation.

UVLO

This function works with the charge mode (MPPT_ENA =H).

In the state the DC/DC converter starts and during the charge operation, when the VDD pin becomes lower than the lower threshold voltage (VUVLOL = 0.2V), UVLO function works and the DC/DC converter stops the operation.

Then when the VDD pin becomes higher than the upper threshold voltage (VUVLOH = 0.3V), the DC/DC converter starts the operation again.

After that, this function is repeated.

VOUT-VDD Voltage Reverse Monitoring

This function works with the charge mode (MPPT_ENA =H).

The detection that the VDD pin is equal to the VOUT pin's voltage or higher is the source to stop the DC/DC control part operation.

Output Current Protection

It has the current limitation function to protect the circuit during the over load current. When the input current for the LX pin reaches LX peak current (ILIMIN_A), the output voltage drops in order to prevent the IC destruction.

State Notification

This function is independent of the MPPT_ENA setting.

The VCC voltage stage, the VOUT voltage state, and the VOUT-VDD voltage reverse state are notified by the DET[1:0] signals.

The state notification is not a power good function.

Table 7-4 Stage Notification of Constant Voltage Mode (MPPT_ENA = L, ENA = H)

Output Signal		State
DET1 Pin	DET0 Pin	Constant Voltage Mode (MPPT_ENA = L, ENA = H)
L	L	VCC terminal \leq VCC detection voltage 1 and VOUT terminal \leq VOUT detection voltage 1
L	H	VCC terminal \geq VCC detection voltage 1 and VOUT terminal \leq VOUT detection voltage 1
H	L	Constant voltage operation: VCC terminal \geq VCC detection voltage 1 and VOUT terminal \geq VOUT detection voltage 1
H	H	VCC terminal \leq VCC detection voltage 1 and VOUT terminal \geq VOUT detection voltage 1

Table 7-5 Stage Notification of Charge Node (MPPT_ENA = H, ENA = H)

Output Signal		State
DET1 Pin	DET0 Pin	Charge Mode (MPPT_ENA = H, ENA = H)
L	L	VCC terminal \leq VCC detection voltage 2 and VOUT terminal \leq VOUT detection voltage 2
L	H	Abnormal stage: Stage that VDD voltage is higher than VOUT voltage ($VOUT < VDD$) ⁽¹⁾
H	L	Protection stop stage: During the period VOUT drop from 4V to 3.7V, after VOUT reaches VOUT detection voltage 3 ($VOUTDETH3 = 4V$) ⁽²⁾
H	H	MPPT operation: VCC terminal \geq VCC detection voltage 2 and VOUT terminal \geq VOUT detection voltage 2


*1: DET[1:0]=[L:L] has the highest priority.

*2: DET[1:0]=[L:H] has the highest priority.

8. Typical Applications Circuit


Constant Voltage Mode

Figure 8-1 Application Circuit of Constant Voltage Mode (MPPT_ENA = L, ENA = H)



Charge Mode

Figure 8-2 Application Circuit of Charge Mode (MPPT_ENA = H, ENA = H)



Parts List
Table 8-1 Parts List

Part number	Value	Description
C1	10 μ F	Capacitor
C2	1 μ F	Capacitor
C3	10 μ F	Capacitor
C4	470 nF	Capacitor
C5	3.3 nF	Capacitor
C6	4.7 nF	Capacitor
C7	100 nF	Capacitor
C8	47 nF	Capacitor
C9	33 pF	Capacitor
C10	10 nF	Capacitor
C11	47 nF	Capacitor
R1	100 k Ω	Resistor
R2	100 k Ω	Resistor
R3	200 k Ω	Resistor
L1	4.7 μ H	Inductor
D1	$V_Z=6.2V$ ($I_Z=250 \mu A$)	Zener diode
D2	$V_Z=6.2V$ ($I_Z=250 \mu A$)	Zener diode

9. Application Notes

Inductor

The MB39C831 is optimized to work with an inductor in the range of 4.7 μ H. Select a value of 4.7 μ H. Also, select an inductor with a DC current rating which can permit the peak current for the inductor.

The peak current for the inductor in steady state operation (I_{LMAX}) can be calculated by the following equation according to the maximum current of harvesters (I_{INMAX}).

$$I_{LMAX} = I_{INMAX} + \frac{V_{VDD} \times (V_{VOUT} - V_{VDD})}{2 \times V_{VOUT} \times F_{OSC} \times L}$$

$$F_{OSC} = 1\text{MHz (Typ)}$$

Harvester (Photovoltaic Power Generator)

In case of photovoltaic (or solar) energy harvesting, use a solar cell with an open-circuit voltage less than 4.75V and the preset output voltage. Electric power obtained from a solar or light is increased in proportion to the ambient illuminance. Silicone-based solar cells are single crystal silicon solar cell, polycrystalline silicon solar cell, and amorphous silicon solar cell. Organic-based solar cells are dye-sensitized solar cell (DSC), and organic thin film solar cell. Crystal silicon and polycrystalline silicon solar cells have high energy conversion efficiency. Amorphous silicon solar cells are lightweight, flexible, and produced at low cost. Dye-sensitized solar cells are composed by sensitizing dye and electrolytes, and are low-cost solar cell. Organic thin film solar cells are lightweight, flexible, and easily manufactured.

Harvester (Temperature Difference Power Generator)

Temperature difference power generators produce electric power keeping temperature difference between the high temperature side and the low temperature side. The temperature difference power generators include the peltier elements utilizing the Seebeck effect and thermopiles that made of thermocouples in series or in parallel.

Sizing of Input and Output Capacitors

Common capacitors are layered ceramic capacitor, electrolytic capacitor, electric double layered capacitor (EDLC), and so on. Electrostatic capacitance of layered ceramic capacitors is relatively small. However, layered ceramic capacitors are small and have high voltage resistance characteristic. Electrolytic capacitors have high electrostatic capacitance from μ F order to mF order. The size of capacitor becomes large in proportion to the size of capacitance. Electric double layered capacitors have high electrostatic capacitance around 0.5F to 1F, but have low voltage resistance characteristics around 3V to 5V. Be very careful with a voltage resistance characteristic. Also, leak current, equivalent series resistance (ESR), and temperature characteristic are criteria for selecting,

Table 9-1 Manufactures of Capacitors

Part Number/Series Name	Type, Capacitance	Manufacture
EDLC351420-501-2F-50	EDLC, 500 mF	TDK Corporation
EDLC082520-500-1F-81	EDLC, 50 mF	
EDLC041720-050-2F-52	EDLC, 5 mF	
Gold capacitor	EDLC	Panasonic Corporation

Energy from harvester should be stored on the C_{in} and C_{out} to operate the application block. If the size of these capacitors were too big, it would take too much time to charge energy into these capacitors, and the system cannot be operated frequently. On the other hand, if these capacitors were too small, enough energy cannot be stored on these capacitors for the application block. The sizing of the C_{in} and C_{out} is important.

First of all, apply the following equation and calculate energy consumption for an application from voltage, current, and time during an operation.

$$E_{\text{Appli.}} [J] = V_{\text{Appli.}} \times I_{\text{Appli.}} \times t_{\text{Appli.}}$$

The energy stored on a capacitor is calculated by the following equation.

$$E_c [J] = \frac{1}{2} CV^2$$

Since the energy in a capacitor is proportional to the square of the voltage, it is energetically advantageous for the boost DC/DC converter, the input voltage, is less than the output voltage, to make the C_{out} larger.

The C_{in} and the C_{out} are sized so as to satisfy the following equation (refer to Figure 9-1). The η , the efficiency of the MB39C831, is determined from the graph of the efficiency shown in Figure 10-1


$$E_{\text{Appli.}} \leq dE_{\text{Cin}} \times \eta + dE_{\text{Cout}}$$

dE_{Cin} and dE_{Cout} are the available energies for the application.

$$dE_{\text{Cin}} [J] = \frac{1}{2} C_{\text{in}} (V_{\text{DD}}^2 - 0.3^2)$$

$$dE_{\text{Cout}} [J] = \frac{1}{2} C_{\text{out}} (V_{\text{OUT}}^2 - V_{\text{OMIN}}^2)$$

Figure 9-1 Example of Energy Harvesting System



Before calculating the initial charging time (T_{Initial}), calculate the total energy (E_{Cin} and E_{Cout}) stored on both C_{in} and C_{out} .

$$E_{\text{Cin}} [J] = \frac{1}{2} C_{\text{in}} \times V_{\text{DD}}^2$$

$$E_{\text{Cout}} [J] = \frac{1}{2} C_{\text{out}} \times V_{\text{OUT}}^2$$

$P_{\text{Harvester}}$ is a power generation capability of a harvester. An initial charging time (T_{Initial}) is calculated by the following equation.


$$T_{\text{Initial}} = \frac{E_{\text{Cin}}}{P_{\text{Harvester}}} + \frac{E_{\text{Cout}}}{P_{\text{Harvester}} \times \eta}$$


Repeat charging time (T_{Repeat}) is calculated by the following equation. The T_{Repeat} become shorter than T_{Initial} .

$$T_{\text{Repeat}} = \frac{dE_{\text{Cin}}}{P_{\text{Harvester}}} + \frac{dE_{\text{Cout}}}{P_{\text{Harvester}} \times \eta}$$

10. Typical Characteristics

Figure 10-1 Typical Characteristics of Constant Voltage Mode (MPPT_ENA = L, ENA = H)








Figure 10-2 Switching Waveforms of Constant Voltage Mode (MPPT_ENA = L, ENA = H)




Figure 10-3 Typical Characteristics of Charge Mode (MPPT_ENA = H, ENA = H)





Figure 10-4 Waveforms of VDD Pin Voltage in Charge Mode (MPPT_ENA = H, ENA = H)




11. Layout for Printed Circuit Board

Note the Points Listed Below in Layout Design

- Place the switching parts ^(*) on top layer, and avoid connecting each other through through-holes.
- Make the through-holes connecting the ground plane close to the GND pins of the switching parts ^(*).
- Be very careful about the current loop consisting of the output capacitor C3, the VOUT pin of IC, and the PGND2 pin. Place and connect these parts as close as possible to make the current loop small.
- The input capacitor C1 and the inductor L1 are placed adjacent to each other.
- Place the bypass capacitor C11 close to VST pin, and make the through-holes connecting the ground plane close to the GND pin of the bypass capacitor C11.
- Place the bypass capacitor C2 close to VCC pin, and make the through-holes connecting the ground plane close to the GND pin of the bypass capacitor C2.
- Draw the feedback wiring pattern from the VOUT_S pin to the output capacitor C3 pin. The wiring connected to the VOUT_S pin is very sensitive to noise so that the wiring should keep away from the switching parts ^(*). Especially, be very careful about the leaked magnetic flux from the inductor L1, even the back side of the inductor L1.

*1: Switching parts: IC (MB39C831), Input capacitor (C1), Inductor (L1), Output capacitor (C3). Refer to Figure 3-1.

Figure 11-1 Example of a Layout Design



12. Usage Precaution

Do Not Configure the IC Over the Maximum Ratings

If the IC is used over the maximum ratings, the LSI may be permanently damaged.

It is preferable for the device to be normally operated within the recommended usage conditions. Usage outside of these conditions can have a bad effect on the reliability of the LSI.

Use the Devices within Recommended Operating Conditions

The recommended operating conditions are the recommended values that guarantee the normal operations of LSI.

The electrical ratings are guaranteed when the device is used within the recommended operating conditions and under the conditions stated for each item.

Printed Circuit Board Ground Lines should be Set up with Consideration for Common Impedance

Take Appropriate Measures Against Static Electricity

- Containers for semiconductor materials should have anti-static protection or be made of conductive material.
- After mounting, printed circuit boards should be stored and shipped in conductive bags or containers.
- Work platforms, tools, and instruments should be properly grounded.
- Working personnel should be grounded with resistance of 250 kΩ to 1 MΩ in series between body and ground.

Do Not Apply Negative Voltages

The use of negative voltages below -0.3V may cause the parasitic transistor to be activated on LSI lines, which can cause malfunctions.


13. Ordering Information

Table 13-1 Ordering Information

Part Number	Package
MB39C831QN	40-pin plastic QFN (LCC-40P-M63)
























14. Marking

Figure 14-1 Marking



15. Product Labels

Figure 15-1 Inner Box Label [Q-Pack Label (4 x 8.5inch)]

		1234	
RoHS	2Li	12345678901234567890 1234567	
Category=	12		
SPEC#	123456789012345678		
IDV	1234567890	PKG	123456 FULL CNTR QTY 1234
			
(1P) MFR#	123456789012345678901234		
(P) OPN	123456789012345678901234		
(1Z) BOX ID			
LOT#	1234567		
HU		123	BOX OF 123
HULN	1234567890123		
(1T) BATCH#	1234567000 		
			
12345678901234567890123		123456789012345	
			
SEAL DC	12345678	TTL QTY (Q)	12345 
ASSEMBLED IN:	12	1234567890123456789012345	
12345678901234567890			
12345678901234567890			
12345678901234567890			
123456789012345			
(9D)M/C:	001HH071	(7Q)QTY:	02500PC
			
12345678	12345678	12345678	1234567
			
12345678	12345678	12345678	1234567
			
12345678	12345678	12345678	1234567
			
12345678	12345678	12345678	1234567
			
12345678	12345678	12345678	1234567
			
12345678	12345678	12345678	1234567
			
12345678	12345678	12345678	1234567


Label spec : Conformable JEDEC
Barcode form : Code 39


Ordering Part Number (P)+Part No.


Quantity


Mark lot information


Figure 15-2 Al(Aluminum) Bag Label [2-in-1 Label (4 × 8.5inch)]







(P) OPN: 123456789012345678901234








(1P) MFR# 123456789012345678901234



(1T) BATCH#
 1234567 000



SEAL DC: 12345678
 123456789012345
 (9D)M/C: 001111021



(7Q)QTY: 02500PC


12345678 12345678

 12345678 12345678

 12345678 12345678

 12345678 12345678

 12345678 12345678

 12345678 12345678


12345678 1234567

 12345678 1234567

 12345678 1234567

 12345678 1234567

 12345678 1234567

 12345678 1234567


(Q) TTL QTY: 1234


LOT# 1234567 BAG ID: 1234 QTY: 1234




(Z) BAG ID: 

Ordering Part Number (P)+Part No.

Mark lot information

Quantity

Caution JEDEC MSL, if available.

CAUTION

This Bag Contains
MOISTURE SENSITIVE DEVICES

JEDEC LEVEL

3


JEITA RANK

E

Category - 12

1. Calculated shelf life in sealed bag: 12 months at < 40 °C and < 90 % relative humidity (RH)
2. Peak package body temperature: 123 + 0 °C / - 5 °C
3. After bag is opened, devices that will be subjected to solder reflow or other high temperature process must:
 - a) Mounted within 1234567890 of factory conditions < 30 °C / 70 % RH, OR
 - b) Stored per J-STD-033
4. Devices require bake, before mounting, if:
 - a) Humidity Indicator Card is > 10 % for level 2a - 5a devices or > 60 % for level 2 devices when read at 23 °C ± 5 °C
 - b) 3a or 3b not met
5. If baking is required, devices may be baked for 24 hours at 125 °C ± 5 °C. Refer J-STD-033 for shorter time durations, if applicable

Note: If device containers cannot be subjected to high temperature or shorter bake times are desired, reference IPC/JEDEC J-STD-033 for bake reference

Bag Seal Date : 1234567 

(If blank, see adjacent bar code label)

Note: Level and body temperature defined by IPC/JEDEC J-STD-020 for JEDEC and EIAJ-ED 4701/300 for JEITA

Document Number: 002-08404 Rev *A

Page 31 of 40

Figure 15-3 Reel Label [Reel Label (4 × 2.5inch)]




Figure 15-4 Reel Label [Dry Pack & Reel Label (4 × 2.5inch)]












Figure 15-5 Outer Box Label [Shopping Label (4 x 8.5inch)]

Quantity		Ordering Part Number : (1P)+Part No.	
(3S) PKG ID: 80000599 		FROM: Spansion LLC and its affiliates 315 DeGuigne Drive, P.O. Box 3453 SUNNYVALE, CA 94088-3453 SHIP TO: 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890 1234567890123456789012345678901234567890	
(1P) MFR P/N: 123456789012345678901234 		(4L) CTRY OF ORIGIN:  12 123456789012345	
(Q) QUANTITY:  12345678 EA		PACKAGE WEIGHT: 12345678 LB PRINTED: 123456 PACKAGE COUNT: 12345 OF 12345	
(K) TRANS ID: 12345678901234567890123456789012345 		DESC: I. C. HU NO. 1234567890123 	
(P) CUST PROD ID: 123456789012345678901234 		CTRY OF DIFFUSION: 12 12 12 12 12 12 ASSEMBLED IN: 123456789012345 DEL NO. 80000599 	

16. Recommended Mounting Conditions

Table 16-1 Recommended Mounting Conditions

Items	Contents	
Method	IR(Infrared Reflow) / Convection	
Times	3 times in succession	
Floor life	Before unpacking	Please use within 2 years after production.
	From unpacking to reflow	Within 7 days
	In case over period of floor life ^(*)	Baking with 125°C+/-3°C for 24hrs+2hrs/-0hrs is required. Then please use within 7 days (Please remember baking is up to 2 times).
Floor life condition	Between 5°C and 30°C and also below 60%RH required. (It is preferred lower humidity in the required temp range.)	

*1: Concerning the Tape & Reel product, please transfer product to heatproof tray and so on when you perform baking. Also please prevent lead deforming and ESD damage during baking process.

Figure 16-1 Recommended Mounting Conditions






Table 16-2 Recommended Mounting Conditions (J-STD-020D)

(Temperature on the top of the package body is measured.)

260°C Max.	
TL to TP: Ramp Up Rate	3°C/s Max.
TS: Preheat & Soak	150°C to 200°C, 60s to 120s
TP - tP: Peak Temperature	260°C Down, within 30s
TL – tL: Liquidous Temperature	217°C, 60s to 150s
TP to TL: Ramp Down Rate	6°C /s Max.
Time 25°C to Peak	8min Max.

17. Package Dimensions

<p style="text-align: center;">40-pin plastic QFN</p>  <p style="text-align: center;">(LCC-40P-M63)</p>	Lead pitch	0.50 mm	
	Package width × package length	6.00 mm × 6.00 mm	
	Sealing method	Plastic mold	
	Mounting height	0.90 mm MAX	
	Weight	0.10 g	



18. Major Changes

Page	Section	Change Results
Preliminary 0.1 [June 14, 2013]		
-	-	Initial release
Revision 1.0 [November 18, 2013]		
8	6.Block Diagram	Added capacitor
9	7.Absolute Maximum Ratings	Added the Rating and of Power dissipation and Figure 7-1
11, 12	9.Electrical Characteristics	Divided old table into system in general table and Boost DC/DC converter table. Added ENA=H into the condition on the table. Changed the Input power supply current condition
14	10.Function 10.3 MPPT control	Added more description
16	10.4 Function UVLO	Changed the sentence "This function is independent of MPPT_ENA." to "This function operates in the charge mode."
18	11.Example	Added standard example
19, 20	12.Typical Applications Circuit Circuit	Added D2 and C11
21	Parts list	Added D2 and C11
23	14.Ordering Information	Added "Figures 14-2 EVB ORDERING INFORMATION"
24	15.Marking	Added new
25	16.Product Label	Added new
26	17.Recommended Mounting Conditions	Added new
-	-	Company name and layout design change
Revision 2.0 [August 29, 2014]		
11, 12	9. Electrical Characteristics Table 9-1, Table 9-2	The table of the electrical characteristics was divided into that of the constant voltage mode and that of charge mode
15	10.2 Start-up/Shut-down sequence Figure 10-1	Added the sequences of MPPT_ENA, ENA, DET1, and DET0 pins.
17	10.2 Start-up/Shut-down sequence Figure 10-2	Added the sequences of MPPT_ENA, ENA, DET1, and DET0 pins.
19	10.4 Function description Table 10-2, Table 10-3	The table of the preset output voltage and the MPPT setting was divided into that of the preset output voltage and that of the MPPT setting.
21	10.4 Function description State notification Table 10-4, Table 10-5	The table of the state notification was divided into that of the constant voltage mode and that of charge mode
25, 26	12. Application Notes	Added the 12. Application Notes
27 to 31	13. Typical Characteristics	Added the 13. Typical Characteristics
32	14. Layout for Printed Circuit Board	Added the 14. Layout for Printed Circuit Board
36 to 39	18. Product Labels	Changed the 18. Product Labels
Revision 3.0 [October 10, 2014]		
3	1. Description	Made a change in the sentence. (MPPT) → (MPPT: Maximum Power Point Tracking)

21	10.4 Function description State notification	Added a following sentence. "The state notification is not a power good function"
24	11. Typical Applications Circuit Table 11-1 Parts list	Made a correction in the part number C6. 4.7 pF → 4.7 nF
26	12. Application Notes Figure 12-1	Added a note in the "Figure 12-1 Application example using the power gating"

Page	Section	Change results
37	19. Recommended Mounting Conditions Table 19-1	Made a correction in the floor life condition. 70%RH → 60%RH
Revision 4.0		
7	5. Pin Descriptions	Added descriptions for all N.C. pins in "Table 5-1 Pin descriptions" "Non connection pin" → "Non connection pin (Leave this pin open)"
11	9. Electrical Characteristics 9.1 Electrical Characteristics of Constant Voltage Mode	Changed the parameter names in "Table 9-1" "Input power supply current" → "Current dissipation 1 " "Current dissipation" → "Current dissipation 2 "
12	9. Electrical Characteristics 9.2 Electrical Characteristics of Charge Mode	Changed the parameter names in "Table 9-2" "Current dissipation" → "Current dissipation 2 " Deleted the rows of the "Input power supply current" from "Table 9-2"
12	9. Electrical Characteristics 9.3 Electrical Characteristics of Boost DC/DC Converter	Deleted the "**2" annotation
13	10. Function 10.1 Outline of Operation	Updated the "10.1 Outline of Operation"
14, 15	10. Function 10.2 Start-up/Shut-down Sequence	Updated the "10.2 Start-up/Shut-down Sequence"
16, 17	10. Function 10.3 MPPT Control	Updated the "10.3 MPPT Control"
18 to 20	10. Function 10.4 Function Description	Updated the "10.4 Function Description"
24, 25	12. Application Notes	Added the equation according to the maximum current in the "Inductor" part. Added the "Table 12-1 Manufactures of Capacitors" Deleted the description of the power gating from "Figure 12-1"
26 to 30	13. Typical Characteristics	Updated the "13. Typical Characteristics" Replaced the efficiency data in "Figure 13-1" "Efficiency vs IOU" → "Efficiency vs Inductor current"
32	16. Ordering Information	Deleted the "Table 16-2 EVB Ordering information"

NOTE: Please see "Document History" about later revised information.

Document History

Document Title: MB39C831 Ultra Low Voltage Boost Power Management IC for Solar/Thermal Energy Harvesting Datasheet

Document Number: 002-08404

Revision	ECN	Orig. of Change	Submission Date	Description of Change
**	—	TAOA	01/30/2015	Migrated to Cypress and assigned document number 002-08404. No change to document contents or format.
*A	5121759	TAOA	02/04/2016	Updated to Cypress template

Sales, Solutions, and Legal Information

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at [Cypress Locations](#).

Products

Automotive	cypress.com/go/automotive
Clocks & Buffers	cypress.com/go/clocks
Interface	cypress.com/go/interface
Lighting & Power Control	cypress.com/go/powerpsoc
Memory	cypress.com/go/memory
PSoC	cypress.com/go/psoc
Touch Sensing	cypress.com/go/touch
USB Controllers	cypress.com/go/USB
Wireless/RF	cypress.com/go/wireless
Spansion Products	cypress.com/spansion products

PSoC® Solutions

[psoc.cypress.com/solutions](#)

[PSoC 1](#) | [PSoC 3](#) | [PSoC 4](#) | [PSoC 5LP](#)

Cypress Developer Community

[Community](#) | [Forums](#) | [Blogs](#) | [Video](#) | [Training](#)

Technical Support

[cypress.com/go/support](#)

Cypress®, the Cypress logo, Spansion®, the Spansion logo, MirrorBit®, MirrorBit® Eclipse™, ORNAND™, Easy DesignSim™, Traveo™ and combinations thereof, are trademarks and registered trademarks of Cypress Semiconductor Corp. ARM and Cortex are the registered trademarks of ARM Limited in the EU and other countries. All other trademarks or registered trademarks referenced herein are the property of their respective owners.

© Cypress Semiconductor Corporation, 2015-2016. The information contained herein is subject to change without notice. Cypress Semiconductor Corporation assumes no responsibility for the use of any circuitry other than circuitry embodied in a Cypress product. Nor does it convey or imply any license under patent or other rights. Cypress products are not warranted nor intended to be used for medical, life support, life saving, critical control or safety applications, unless pursuant to an express written agreement with Cypress. Furthermore, Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress products in life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

This Source Code (software and/or firmware) is owned by Cypress Semiconductor Corporation (Cypress) and is protected by and subject to worldwide patent protection (United States and foreign), United States copyright laws and international treaty provisions. Cypress hereby grants to licensee a personal, non-exclusive, non-transferable license to copy, use, modify, create derivative works of, and compile the Cypress Source Code and derivative works for the sole purpose of creating custom software and or firmware in support of licensee product to be used only in conjunction with a Cypress integrated circuit as specified in the applicable agreement. Any reproduction, modification, translation, compilation, or representation of this Source Code except as specified above is prohibited without the express written permission of Cypress.

Disclaimer: CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes without further notice to the materials described herein. Cypress does not assume any liability arising out of the application or use of any product or circuit described herein. Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress' product in a life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

Use may be limited by and subject to the applicable Cypress software license agreement.