



FIGURE A
 MAXIMUM OUTPUT CURRENT OF ANY DUAL INPUT VOLTAGE OR VOLTAGE DOUBLER UNIT OPERATED AT LOWER INPUT VOLTAGE.

* MAXIMUM OUTPUT CURRENT IN OUTPUT VOLTAGE RANGE FROM 0 TO 25% ABOVE LINE VOLTAGE. AT HIGHER OUTPUT VOLTAGES, OUTPUT CURRENT MUST BE REDUCED ACCORDING TO RATING CURVE, FIGURE A.

++ MAXIMUM KVA AT MAXIMUM OUTPUT AND CORRESPONDING DE-RATED CURRENT. MAXIMUM KVA AT LOWER OUTPUT VOLTAGES MAY BE CALCULATED FROM RATING CURVE, FIGURE A.

V.D. = VOLTAGE DOUBLER.

WIRING	INPUT		OUTPUT		SHAFT ROTATION FOR VOLTAGE INCREASE	TERMINAL CONNECTIONS FOR INCREASING VOLTAGE AS VIEWED FROM TOP		
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		INPUT	OUTPUT	
				MAX. AMPS				MAX. KVA
SINGLE PHASE PARALLEL	240	50/60	0-240	168	40.3	CW	1-4	1-D
			0-280	168	47.0	CW	1-2	1-D
	120	50/60	0-280	168-72 V.D.	20.4 ++	CW	1-5	1-D

UNLESS OTHERWISE SPECIFIED, TOLERANCE IS #	UNITS	TITLE:	STACO ENERGY PRODUCTS CO. A COMPONENTS CORPORATION OF AMERICA COMPANY DAYTON, OHIO U.S.A.
DECIMALS .12 Holes .03 ANGLES 1° DRAFT 1-1/2°	IN [mm]	SPEC. CONTROL DRAWING VARIABLE TRANSFORMER TYPE: 5021E-6P	
MATERIAL:	ALL DIMENSIONS APPLY AFTER PLATING	DATE: 3/25/98	DO NOT SCALE DWG.
DRAWN BY: TIM RAU	CHECKER:	DATE:	CUSTOMER APPROVAL:
ENGINEER:	SCALE: .2=1	DATE:	DATE:
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.		WEIGHT APPROX.	CODE IDENT. NO. 83008
		SCALE: .2=1	DWG. NO. 031-7500
		SHEET 1 OF 1	